



CINE SYNC™ CP-1 FOOTAGE/FRAME COUNTER

The **CP-1** is a small footage counter that can replace mechanical counters on editing machines. The **CP-1** is an electronic counter that makes no noise while running. It features a large LED display, automatic stop and selectable input pulse rates. Footage is displayed in negative numbers when running in reverse.

FEATURES

DISPLAYS 35mm footage and frames. Can be configured for 16mm.
0.3 inch high LED display with leading zero suppression.

STOP can be switch activated for editing tables for zero stop.

EXTERNAL HOLD to inhibit count when transports are not engaged.

BATTERY backed up memory when power is off.

SWITCH selectable pulse rates work with most standard film machines.

SPECIFICATIONS

POWER Input +9 to +24 volts at 170 ma.

INPUT Bi-phase 5 volt logic.

Rates Include 1, 2, 2.5, 4, 5, 8, 10, 16, 25, 40, 50, and 80 pulses per frame.

OUTPUT +5 volts for encoder power. +5 volt logic at 100 ma for stop.

EXTERNAL +5 or 0 volt logic for remote hold input.

PC BOARD size 1.25 x 5.25 excluding switch.
Metal case is optional.

Denecke, Inc.

5417-B Cahuenga Blvd. • North Hollywood, CA 91601
(818) 766-3525 • (800) 866-3525